



HS4	HS3	HS2	HS1	Handset 4M2	Handset 4M4	Handset 6M2	Handset 6M4
0	0	0	0	(stop)	(stop)	(stop)	(stop)
0	0	0	1	Up1	Up1	Up 1	Up1
0	0	1	0	Down 1	Down 1	Down 1	Down 1
0	0	1	1	Memo	Memo	Button 2	Button 2
0	1	0	0	Button 1	Button1	Button 1	Button 1
0	1	0	1	Up1	Up2	Up1	Up2
0	1	1	0	Button 4	Button 4	Memo	Memo
0	1	1	1	Reserved	Reserved	Reserved	Reserved
1	0	0	0	Button 2	Button 2	Button 3	Button 3
1	0	0	1	Down 1	Down 2	Down 1	Down 2
1	0	1	0	Button 3	Button 3	Button 5	Button 5
1	0	1	1	Reserved	Reserved	Reserved	Reserved
1	1	0	0	Not used	Not used	Button 4	Button 4
1	1	0	1	Reserved	Reserved	Reserved	Reserved
1	1	1	0	Not used	Not used	Button 6	Button 6
1	1	1	1	Reserved	Reserved	Reserved	Reserved

Specification of the handset inputs of the Movetec Compact 2 and Movetec Compact 3 control boxes.

The connections have to be potentialfree via relais for example.

Parallel interface:

All HS1-4 inputs are having an internal pull-down resistor with 10k. The 5V supply is capable to deliver 150mA.

RX: not used at parallel interface

Drawn by thk	Scale	Used in: Specification of handset inputs of Movetec Compact 2 + 3 control boxes.	Date 16.12.2019.
		Compact 2 and Compact 3 Handset PIN assignment	Norm. (DIN)
		This drawing remains property of MOVETEC and may not be copied or given to any other party for information or use without our written consent.	Drawing number: MAC-EL5.0/12/19